

Handset Intercom with Privacy

STATION

13

TD-Z/A



- 7 or 13 identical station, full trunk all-master configuration
- No break-in call
- Homerun wiring to CT-Z

- Zone page(s) in lieu of station(s)



TD-6Z/A
Master station for
7-station system



TD-12Z/A
Master station for
13-station system




CT-63Z for TD-6Z/A (photo)
CT-195Z for TD-12Z/A

Options



PD-1 Zone page adaptor
PD-2 Zone talkback page adaptor (photo)
→ P.72

Communication network & wiring



System Components

- TD-6Z/A:** 6-call master for max. 7-station system
- TD-12Z/A:** 12-call master for max. 13-station system
- CT-63Z:** Terminal board for TD-6Z/A
- CT-195Z:** Terminal board for TD-12Z/A
- Power supply:** PS-12A, PS-12B

Write wire color code and connect station #1 on 1st row of terminals assigned.

#1 TD-6Z/A #2 TD-6Z/A #3 TD-6Z/A

ea. 9

CT-63Z

PS12



STATION No.

CT-63Z prewired internally


PS12 to: PD-1 or PD-2

PS12: PS-12A, PS-12B
★ Door station can not be connected with CT-Z.

TD-6Z/A
TD-12Z/A



CT-63Z



Specifications (TD-Z/A)

Power source	12V DC, 90mA per channel	
Power supply	PS-12A, PS-12B	
Communication	Depress a selector and CALL to ring opponent.	
Wiring	TD-6Z/A: 10 wires homerun to CT-63Z TD-12Z/A: 16 wires homerun to CT-195Z	
Distance	0.65mmø	0.8mmø
• Homerun to CT-Z	300m	460m